

## 尊敬的用户：

感谢您选购得胜KP系列音箱，该音箱内置二分频设计，外观简约大气，质感出众；音质方面，层次清晰、细腻耐听，适用于会议以及基础扩声应用工程。为了您能够更好地了解使用本产品，建议您在使用前仔细阅读本说明书。

若存在有疑问或者您有宝贵的建议，可通过拨打得胜官方服务热线 400 618 5575或微信扫描二维码关注得胜讲解器公众号与我们联系。



## ■ 产品特性

- KP系列为内置两分频的全频音箱，单元采用了一只人声低频厚实的低音扬声器，和一只音色甜美细腻的高音；
- 分频器的元件采用了损耗值较低的高品质薄膜电容，以及散热性能良好的水泥电阻，使分频网络稳定，音质出众；
- 音箱整体音色层次均匀，无论在音乐还是人声的表现上，都能突显自然、清晰的音质特点；在开发过程中，也反复配套试用了多款动圈麦克风和电容麦克风的人声语音表现，均有良好的语音音质效果。

## ■ 标准配置

- KP-6音箱 2只      KP-8/KP-10音箱 2只  
 壁挂 1只      说明书 1份  
 说明书 1份
- KP-12/KP-15音箱 1只  
 说明书 1份

## ■ 适用场合

- 适用于会议室、报告厅等场所

## ■ 注意事项

1. 确保功率放大器和音箱的功率、阻抗相匹配，失衡搭配可导致设备损坏或音质效果不佳。
2. 使用时根据实际需要把拨动开关打到相应的模式，以保证所需要的音质。
3. 使用时，音箱正面朝向听众区域，以确保获得较佳听感。
4. 音箱的安装需由专业工程人员进行，应固定牢靠，并选择安装在不易碰触的位置。
5. 搬运音箱时，请小心轻放，保护好音箱不受损坏。

## ■ 技术参数

型号	KP-6	KP-8	KP-10	KP-12	KP-15
功率 (AES)	90W	100W	200W	300W	500W
阻抗	6Ω	8Ω	8Ω	8Ω	8Ω
频率响应 (±3dB)	70Hz-19kHz	60Hz-18kHz	65Hz-20kHz	55Hz-18kHz	45Hz-20kHz
灵敏度 (1W/1M)	92dB	92dB	94dB	95dB	97dB
覆盖度	H90°*V60°	H90°*V60°	H90°*V60°	H90°*V60°	H90°*V60°
最大声压级	106dB	114dB	121dB	123dB	126dB
分频模式	两分频	两分频	两分频	两分频	两分频
吊挂/安装	壁挂	支撑/吊挂	支撑/吊挂	支撑/吊挂	支撑/吊挂
接线方式	按压式接线盒	1×NL4speakon (1+、1-)			
箱壳	9mm中纤板	12mm中纤板	12mm中纤板	12mm中纤板	15mm中纤板
表面处理	黑色小点漆	黑色小点漆	黑色小点漆	黑色小点漆	黑色小点漆
单元	高频：3"×1(13芯)	高频：3"×1(13芯)	高频：1"×1(25芯)	高频：1"×1(25芯)	高频：1"×1(25芯)
低频	6.5"×1(25芯)	8"×1(25芯)	10"×1(35芯)	12"×1(50芯)	15"×1(50芯)
产品尺寸 (W*D*H)	220*205*300mm	230*246*350mm	277*270*445mm	338*345*518mm	412*423*609mm
净重	约3.1kg/只	约4.7kg/只	约7.15kg/只	约11.2kg/只	约18.2kg/只

注：以上数据由得胜实验室测试得到，并拥有最终解释权！

## ■ 安全警示

为避免电击、高温、着火、辐射、爆炸、机械危险以及使用不当等可能造成的人身伤害或财产损失，使用本产品前，请仔细阅读并遵守以下事项：

1. 使用产品时请确认所连设备与本产品是否匹配以及合理调整音量大小，不要在超过产品功率及大音量下长时间使用，以免造成产品异常；
2. 使用中若发现有异常（如冒烟、异味等），请立即关闭电源开关并拔掉电源插头，然后将产品送售后服务网点检修；
3. 消费者若使用电源适配器供电，则应购买配套使用获得CCC认证并满足标准要求的电源适配器；
4. 本产品及配件都应放置在室内干燥通风处，请勿长期存放在潮湿、灰尘多的环境，使用中避免靠近火源、雨淋、进水、过度碰撞、抛掷、振动本机及覆盖通风孔，以免损坏其功能；
5. 使用该产品时需遵守相关安全规定，法律法规明确禁止使用场合请勿使用本产品，以免导致意外事故；
6. 请不要自行拆卸改装或维修，以防止出现人身伤害，如有问题或服务需求请联系当地售后服务网点跟进处理。

## ■ 环保说明

产品中有毒有害物质或元素名称及含量标识表

部件名称	有毒有害物质或元素									
	铅 (Pb)	汞 (Hg)	镉 (Cd)	六价铬 (Cr(VI))	多溴联苯 (PBB)	多溴二苯醚 (PBDE)	邻苯二甲酸二丁酯 (DBP)	邻苯二甲酸二己酯 (DEHP)	邻苯二甲酸丁基酯 (BBP)	邻苯二甲酸二(2-乙基己基)酯 (DEHP)
塑料部件	○	○	○	○	○	○	○	○	○	○
金属部件	×	○	○	○	○	○	○	○	○	○
电路板组件	×	○	○	○	○	○	○	○	○	○
线缆	×	○	○	○	○	○	○	○	○	○

注1：○：表示该有害物质在该部件所有均质材料中的含量均不超过国家电子产品有害物质限制使用国家标准要求。  
 ×：表示该有害物质至少在该部件的某一均质材料中的含量超出国家电子产品有害物质限制使用国家标准要求。  
 注2：以上未列出的部件，表明其有害物质含量均不超过国家电子产品有害物质限制使用国家标准要求。

此标志为产品的环保使用期限标志。  
 且此标志使用期限只适用于产品正常工作时的温度和湿度等条件。

### 注意事项：

1. 本单为保修凭证，请用户妥善保管，如有遗失，恕不保修或退换。
2. 保修期限：购买之日起十二个月内。
3. 除了不可抗力事件损坏外，由本公司负责，免费维修。
4. 如属保管不善或使用不当造成的损坏，维修点将酌情收费。
5. 擅自拆卸维修者，不予保修。
6. 以上保修条款仅限于中国市场适用（不含港澳台地区）。

### 产品服务保证书

姓名：\_\_\_\_\_ 电话：\_\_\_\_\_ 地址：\_\_\_\_\_

商品：\_\_\_\_\_ 型号：\_\_\_\_\_ 购买日期：\_\_\_\_\_年\_\_月\_\_日

维修记录栏 (由维修员填写)	维修员签名	日期

◆广东得胜电声有限公司 ◆电话：400-6828-333 ◆地址：中国广东省惠州市博罗县龙溪街道夏寮村委会大门村夏寮(得胜创业园)



## Dear Customer,

Thank you for purchasing Takstar KP Series Speakers. These speakers boast built-in two-way frequency division, simple elegant appearance and great texture. It delivers clear, delicate sound, ideal for meetings and basic sound reinforcement. In order to better understand and use the product, please read this manual carefully. If you have any questions or suggestions, please contact our local dealer.

## ■ Features

- The KP Series is full-range speakers with built-in two-way frequency division, featuring one woofer for rich vocal low frequencies and one tweeter with sweet, delicate sound.
- Its crossover uses low-loss high-quality film capacitors and heat-resistant cement resistors, ensuring stable crossover and superior sound quality.
- The speaker has balanced sound layers, delivering natural, clear sound for music and vocals. It was repeatedly tested with various dynamic and condenser microphones during development, all achieving good vocal quality.

## ■ Standard Configuration

KP-6	KP-8/KP-10
2 × Speakers	2 × Speakers
2 × Wall Mount Brackets	1 × User Manual
1 × User Manual	
KP-12/KP-15	
1 × Speaker	
1 × User Manual	

## ■ Applications

- Ideal for conference rooms, lecture halls, and other similar venues

## ■ Specifications

Model	KP-6	KP-8	KP-10	KP-12	KP-15
Power (AES)	90W	100W	200W	300W	500W
Impedance	6Ω	8Ω	8Ω	8Ω	8Ω
Frequency Response (±3dB)	70Hz-19kHz	60Hz-18kHz	65Hz-20kHz	55Hz-18kHz	45Hz-20kHz
Sensitivity (1W/1M)	92dB	92dB	94dB	95dB	97dB
Coverage Angle	H90°*V60°	H90°*V60°	H90°*V60°	H90°*V60°	H90°*V60°
Maximum SPL	106dB	114dB	121dB	123dB	126dB
Crossover Mode	Two-Way	Two-Way	Two-Way	Two-Way	Two-Way
Suspension/Mounting	Wall Mount	Bracket/Suspension	Bracket/Suspension	Bracket/Suspension	Bracket/Suspension
Connection Type	Push-Type Terminal Box	1×NL4speakon (1+, 1-)			
Cabinet	9mm MDF	12mm MDF	12mm MDF	12mm MDF	15mm MDF
Surface Treatment	Black Speckled Paint	Black Speckled Paint	Black Speckled Paint	Black Speckled Paint	Black Speckled Paint
Driver	HF: 3"×1 (13mm Coil)	HF: 3"×1 (13mm Coil)	HF: 1"×1 (25mm Coil)	HF: 1"×1 (25mm Coil)	HF: 1"×1 (25mm Coil)
LF	6.5"×1 (25mm Coil)	8"×1 (25mm Coil)	10"×1 (35mm Coil)	12"×1 (50mm Coil)	15"×1 (50mm Coil)
Product Dimensions (W*D*H)	220*205*300mm	230*246*350mm	277*270*445mm	338*345*518mm	412*423*609mm
Net Weight	Approx. 3.1kg/unit	Approx. 4.7kg/unit	Approx. 7.15kg/unit	Approx. 11.2kg/unit	Approx. 18.2kg/unit

Note: The above data are measured by Takstar laboratory which has the final interpretation right!

## ■ Cautions

1. Ensure the power amplifier and speaker are matched in power and impedance; mismatch may cause damage or poor sound.
2. Set the toggle switch to the correct mode as needed for optimal sound.
3. Face the speaker front toward the audience area for best listening experience.
4. The installation of the speaker must be carried out by professional engineers. It should be securely fastened and installed in a location that is not easily touched.
5. When moving the speaker, handle with care to prevent damage to the speaker.

## ■ Safety Instructions

To avoid electric shock, overheat, fire, radiation, explosion, mechanical risk and injury or property loss due to improper use, please read and observe the following items before use:

1. Please check if the power of the connected equipment matches with that of this product before operation. Adjust the volume to proper level during operation. Do not operate at over-power or high-volume level for extended time to avoid product malfunction.
2. If there is any abnormality during use (e.g., smoke, strange odor), please kill the power switch and unplug from power source, then send the product to the local after-sales service for repair.
3. Power adapter used, if any, should be approved by CCC certification or similar standards and comply with the power supply requirements.
4. Keep this product and its accessories in a dry and ventilated area. Do not store in a humid or dusty area for extended time. Keep away from fire, rain, liquid intrusion, bumping, throwing, vibrating, or from blocking any ventilation openings, to prevent malfunction.
5. Please abide by safety rules during operation. Do not use the product in places prohibited by laws or regulations to avoid accident.
6. Do not disassemble or repair the product unauthorized to avoid injury. If you have any questions or require any services, please contact our local after-sales service.